

GUB431

4-Port USB 2.0 Automatic Printer Switch



IOGEAR's USB 2.0 Automatic Printer Switch allows four PCs and / or Macs to share one printer or multi-function printer. Simply submit a print job and the printer automatically* switches to the preferred computer. The switch also enables four computers to easily share one external hard drive, scanner, or any USB device. No more plugging and unplugging between computers.


* Automatic switch function is software based and only available with USB printer or the printer function of a multi-function printer. For connecting and using other types of USB devices, you can switch by using the push-button on the USB switch or with the included software.

- Automatically* switch from one computer to another when connecting to a USB printer or multi-function printer
- Easily share a USB 2.0 device between PC and Mac without a network setup
- Simply press a button to switch a USB device between computers - No software installation required
- Active-port LED lights indicate which computer has access to the USB device
- Switch-lock function prevents other users from switching the USB device and ensures data access consistency
- USB 2.0 support with data transfer rate up to 480Mbps and USB 1.1 backward compatible
- No external power supply needed



How does it work?

- Connect your USB device (i.e. printer, external hard drive, or scanner) to the USB-A connector
- Connect your computers (PC or Mac) to the USB-B connector
- Simply push the button to swap or enable automatic* switch between four computers



Requirements

- For PC Users
- Windows XP, Windows Vista, Windows 7, Windows 8/8.1, 10
 - Available USB 2.0 port
 - Chrome Book
 - Linux®, Unix and other USB supported systems*
- *Additional drivers and support may be needed

Package Contents

- 1 x USB 2.0 Auto Switch
- 1 x 6 ft. USB A-B Cable
- 1 x User Manual
- 1 x Application CD
- 1 x Registration / Warranty Card

- For MAC Users
- Mac 8.6 - Mac 10.10.
- Requires OS X for USB 2.0 support
- Available USB 2.0 port

Specifications

Function	GUB431	Dimensions	GUB431
Computer Connections		POP Information	
Direct	USB Type-A	10" Peg Hook	4
Connectors		6" Peg Hook	3
Console	1	Unit Dimensions	
Device Side	4	Width	4
Environment		Height	3
Humidity	0-80% RH	Depth	1
Operation Temperature	41 to 104 degree Fahrenheit	Unit Package Dimensions	
Storage Temperature	-4 to 140 degree Fahrenheit	Width	6
LEDs		Height	7.25
Port Status	Green - Online / Orange - Locked	Depth	2.25
Host Status	Orange - Online	Master Carton	
Operating System Support		Width	8
Windows ZP and above; Mac: 10.4.5, 10.5 and above		Height	7
Power Consumption		Depth	15
DC 5V, 2.5W		Master Carton Qty.	6
Power Supply		Weight	
USB Bus powered		Master Carton Wt.	5 lb.
		Unit Pack Wt.	0.7 lb.
		Unit Wt.	0.2 lb.